<u>PUSHSAFER</u> is a third party service meant to receive push notification on mobile phones or computers .

From fw release 2.1.1, ScanLabs WiFi Dongle is enhanced with this new service aim to send push notifications in one or more of the following conditions:

- Daily Report Sent when SunSut comes
- Daily Report Sent when SunRise comes
- Report when battery reaches 100% SOC
- Report when one or more Alarms is/are detected

<u>*Pushsafer*</u> it comes with a very interesting offer, as of today 0.99€ for 1000 notifications or 1.99€ for 2200 notifications ! looks nice don't you ?

For the sake of testing , <u>*Pushsafer*</u> offers 50 notifications for free, it's just a matter to create an account - install <u>*Pushasafer*</u> app on your mobile(s) and or PC(s) - setup the ScanLabs dongle accordingly and you are done.

Let's follow these steps to enable and test the *Pushsafer* service

4.3.1 - create your free account on *pushsafer.com* you will have 50 free push to test the service

JSHASAFER	
What does l'ushasher do	Login
With Pushsater you can easy and safe send and	USERNAME OR E-MAIL ADDRESS
securely to your iPhone. IPad. Android. Windows	Jaemana or E-mail Address
mobile or Windows desidop device, Telegram and to	PRESHOPD
your browser (Chrome, Firefox, Edge, Opera &	Passevord
Yandex)I	Forgot your usemame or password?
Send & receive push-notifications to your devices by	
EMAIL, through a simple URL / LINK or with our API	Login
Offers solutions for many esca filluities, for example: home automation alerts, ip camera motion detection, server monitoring, sheduled reminder and everything else you want to be reminded	Register Now for Free
It is easy to set up! Many plugine available!	DUL HUS
Test Puchealer now	Full Name
	1/27DMAR
	Destroyers
	CANA ACCESS
fow does l'ushasher works	amalifizers/doc.com
How To	LANCING
	Emplot V
יביג אָיאָ 🖶 🖬	COUNTRY
	¥
	THEZONE
and Brites	PISSINGED
NO DE CALLA	Passented
	CONFIRMENCONFERD
0 0 BH	Conferen Pressanced
100 000 000	ACCEPTED TERMS
Clienta & Appa	Contracting of Adult Contracting
Android	Create Account

And a local division of the	and Reserved Additional And Reserve Statements Restations Reserve	the second state in the second state of the se
USHASAFER		
DASHBCARD	API Catin Enginteed Devices Online Contract Cont	Groups E-shall Alass D
Registered Devices	Your private key	Parameter
Device Groups Device	\$ cu	Use parameters to configure your push-notification, press the arrange parameters to get a more detailed description.
ACCOUNT PROFILE		* Private or Alias Key*
API-LOG	To receive push-notifications from e-mails, send a message to:	Example: ISA21x21TVsh29xX2000
CLIENTS / APPS	apushsater.com @	a Device
		Single Device ID or Device Group ID or all Devices
EXAMPLES & PLUGINS	Vour extends outplans	e-a = to all devices
nov.	TUE INVERTIGATION OF	d-gs21 = to a device group
740	The subkey is used for sending cross-account messages	d+12 = 10 a single device d+114ATra = to multiple devices of same account
SUPPORT / FORUM	0	
CHANGELOG		• T112#
CUSTOMER REVIEWS		· Pessage *
LANGUAGE English	Your Devices	🖁 * Sound empty * device default Of a number a - 62
LOGOFF		* Vibration empty = device default of a number 1 - 3
	anywing (2) v Intrones - Search:	(only IOS & Android)
	ID - Name received Status Synced Action	E = 1con Standard = 1 or a number 1 - 1x1
	No records to display	🖀 = iron Color Standard = Empty
SOFTWARE		or a Hexadecimal Colorcode, Example: #FF0000
IN GERMANY	Showing B - 0 of 0 entries 4 a	(only Android >5.0, Webders TV & Crent APP)
	Devide De	(only Android, device needs a RGB LED)
Let's Encrypt	reg languar tours creves inspace rate ances	🖉 = URL/LINK (u="RTTps://www.pushsafer.com"
		I uni title ut-"Open Link"
	Device calculas	Open other apps through push notifications by using

4.3.2 - Login, on the main dashboard, copy "YOUR PRIVATE KEY"

- 4.3.3 Go to your ScanLabs SmartBMS WiFi Dongle "Settings" web page
- 1- Select PUSHSAFER Service

Status	Battery	Monitor	Settings	Upgrade
		Config File Version	1 #2	
			<i></i>	
WIFI Mode: AP (WIFI Station Wode)			
SSID: ScanLabsWiFiHotSpot				
WiFi Power [dBm]: 10]			
Static IP:				
Latitude: 45,649601	Longitude: 9,205900	Google maps		
Friday, May 10 2024 08:39:0 Time Zone GMT+: 2	06 Sync with PC			
Submit	_			
	2			
MQTT MODBUS TCF	PUSHSFAER	MISC STORAGE	NERDS	
System Restart ** Factory Re	eset **			

4.3.4 - Setup the dongle with <u>Pushsafer</u> credentials (follow steps 1-5 on the image)

4.3.4.1 Paste your *PushSafer* "PRIVATE KEY"

- 4.3.4.2 Setup your friendly message each push will report
- 4.3.4.3 Select which kind of push you what to get every day
- 4.3.4.4 Enable PUSHSAFER Service
- 4.3.4.5 SUBMIT the settings

Status	Battery	Monitor	Settings	Upgrade
		PUSHSAFER CONFIG		
PUSHSAFER: 2 4 Private KEY: •• Message: My House in Italy Send to: a SunSet Report: 2 SunRise Report: 2 100% SOC Report: 2 Alarm Report: 2 Submit 5	1 2 3	TEST Send Daily Report NOW Send Alarm Report NOW		
BACK to CONFIG				

4.3.5 - using the QRCODE and Links offered on the main page of <u>*PushSafer.com*</u>, install the app on one or more iOS, Android, Windows, Telegram etc login on each instance with the <u>*PushSafer*</u> credentials you have created

Android	Windows 10 (UWP)
Coogle Play	Windows 10/11 Universal App for Smartphone, Tablet & Desktop
iOS (iPhone, iPad, iPod Touch)	
Download on the App Store	

4.3.6 You are now ready to TEST if a push Notification reaches your device/s

Status	Battery	Monitor	
		PUSHSAFER CONFI	G
PUSHSAFER: Private KEY: •• Message: My House in Italy Send to: a SunSet Report: SunRise Report: 100% SOC Report: Alarm Report:		TEST Send Daily Report NOW Send Alarm Report NOW	
Submit			•
BACK to CONFIG		1000 - 1000 - 1	
	AT THIS POINT	YOU SHOUL BE HA	APPY ;-)
SOC 100% Your daily re SOC =100% at time 14.6 Average on 1	port : 3.26am hatteries 3567mv	Pigio 2024 alle ore 17:02 23.446 di 23.447	29 aprile 2024 alle ore 08:18 23:415 di 23:427 08:18 PULF CALL (CALL OF CALL OF CAL
5	17:02	•• * •	
	My House in BMS Alarm P	n Italy leport	
	MAX SOC : 1 CUR SOC : 1 WHEATHER: SUNRISE : 00 SUNSET : 20 BATTERY : 5 CAPACITY : 2 VOLT AVG : 3 VOLT A : 208	00% @ 16:51 00% RELAXING poloudy 8:00 4:50 V , 0.00 A 00 A/h 478 mV mV s Dongle	